



### PRODUCT FEATURES

- Backup device in case of exit sensor failure per BOCA, NFPA, IBC, and VBC code
- SPST 3A wet N/C contacts
- Momentarily pressing the EEB releases the door for 30-seconds
- Re-triggerable for added 30-second release
- Field-selectable 12 VDC or 24 VDC to match lock voltage
- Interchangeable green and red lenses included standard
- MagnaCare® lifetime replacement, no fault warranty

### PRODUCT OPTIONS

- Single gang
- Narrow stile
- EEB2 includes standard lenses plus blue ADA lens
- Illumination kits

### SPECIFICATIONS

- (EEB2, EEB3N only)
- ANSI/UL 294 Listed
  - CSA-C22.2 No.205 Listed
  - CSFM – California State Fire Marshal

# EEB

## Emergency Exit Button

### Redundant Backup Ensures Safe Egress

Install the EEB Emergency Exit Button next to the door to provide additional safety and redundancy as required by code when using a motion detector for a request-to-exit device.

### » MODELS

PART #	Description
<b>EEB2</b>	EEB w/ 30 Sec. Timer - Single Gang, SPST, Grn/Red/Handicap
<b>EEB3N</b>	EEB w/ 30 Sec. Timer - Narrow Stile, SPST, Grn/Red
<b>PB2-LK</b>	Illumination Kit for PB2E, PB5E, EEB2 Series Push Buttons
<b>PB3-LK</b>	Illumination Kit, Grn/Red for PB3E/EEB3N Series



**Note:** Securitron's UL294 certification indicates that when the EEB is used with the XMS Motion Sensor, it meets the NFPA Life Safety Code 101 requirements for exit of access-controlled egress doors.



DUAL VOLTAGE

